

POWER IS OUR WORLD

About Product

IDEA generator sets are designed to be used as backup or continuous power supply. They are subjected to detailed load and performance tests in our production facilities in order to provide ideal performance and safe usage.



Power Output Values


Voltage	Standby Power (ESP)			Prim	Prime Power (PRP)		
	kVA	kW	Ampere	kVA	kW	Ampere	
400/231	2576 kVA	2060,5 kW	3722	2311 kVA	1849 kW	3339,5	


Standby Power (ESP): This rating is for the supply of continuous electrical power at variable load, in the event of utility power failure. No overload is permitted.


Prime Power (PRP): This rating is for the supply of continuous electrical power at variable load. There is no limitation on the annual hours in operation and 10% overload power can be supplied for 1 hour in 12.

Weight And Dimensions

Туре	Width x Length x Height (mm)	Weight (kg)	Fuel Tank (Lt)	Sound dB(A) @7mt
Open	2400x6900x2450 mm	14800 kg	3500 Lt	TBA
Soundproofed	2470x12220x3150 mm	19650 kg	3500 Lt	94









www.ideajenerator.com I info@ideajenerator.com

IDEA

POWER IS OUR WORLD

Engine



Frequency		50 Hz	
Output Rating	kW	2220	
Manufacturer and Model		DAEWOO 16DWG-2500	
Fuel		Diesel	
Injection		Direct	
Aspiration		Turbo Charged & Intercooled	
Cylinders		16	
Bore and Stroke	mm	170 x 195	
Displacement	lt	70,8	
Cooling		Water	
Engine Oil Specification		SAE 15W40	
Compression Ratio		13,5:1	
Engine Oil Capacity(Sump Only)	lt	240	
Coolant Capacity (incl.radiator)	lt	480	
Governor		Electronical	
Air Filter		Dry element	
FUEL CONSUMPTION			
100 % Load	lt/h	453	
75 % Load	lt/h	343	
50 % Load	lt/h	240	
EXHAUST SYSTEM			
Maximum Temperature	°C	ТВА	
Exhaust Gas Flow	m³/min	6 <mark>16</mark> ,8	
Maximum Allowed Back Pressure	kPA	6	
Exhaust Flange Size (Internal Dia.)	mm	220	
AIR SYSTEM			
Intake Air Flow	m³/min	<mark>246,7</mark>	
Total Cooling Air Flow	m³/min	TBA	
STARTING SYSTEM		¥	
Starter Motor	kW	13	
Battery Capacity	Ah	4x160	
Auxiliary Voltage	V	24	

Alternator

Poles	4 pole		
Winding Connections	Star		
Insulation	Class H		
Enclosure	IP23		
Exciter System	Self regulating Brushless		
Voltage Regulator	AVR		
Steady State Voltage Regulation	± 1 %		
Bearing	Single bearing sealed		
Coupling	Flexible disc		
Cooling	Direct drive centrifugal blower fan		





POWER IS OUR WORLD

Control Panel IDP300

The new IDP300 genset controller is a cost effective modular genset controller ready for internet monitoring through plug-in modules.

Its main advantages are multifunctionality, support for multiple topologies, harmonic analysis and detailed power measurements.



Software features are complete with easy firmware upgrade through USB port. The Windows based PC software allows monitoring and programming through USB, RS-485, RS-232, Ethernet and GPRS.

The Rainbow Scada web service allows monitoring and control of an unlimited number of gensets from a single central location.

Optional Equipments

Some Optional Equipment IDEA Provides with Generator Sets;

- Remote radiator applications,
- Automatic fuel filling system,
- Fuel tank, oil pan, instrument panel, alternator, coil heaters,
- Synchronization systems,
- Generator output fuse,
- Mains generator transfer switches,
- Seismic solutions,
- Remote monitoring
- Other requested solutions

Reference Standards

IDEA Generator Sets are CE approved and comply with the following standards;

- Power according to ISO 3046 and ISO 8528
- EN 12100, EN 13857, EN 60204
- 2006/42/CE Machinery Safety
- 2006/95/EC Low Voltage
- 2004/108/CE EMC
- Ambient reference conditions 1000 mbar, 25 °C, 30 % relative humidity ISO8528

All the information in this leaflet is intended for general purposes only. IDEA reserves the right to change the specifications without notice.



www.ideajenerator.com I info@ideajenerator.com